CP 300 Series

Mid-range printing mechanisms for various applications

Specifications	CP305	CP324
----------------	-------	-------

Print method	Thermal	Thermal
Number of dots	576	576
Resolution (dots/mm)	8	8
Printing width (mm)	72 / 2x33	72 / 2x33
Paper width (mm)	80 / 2x 39	80 / 2x 39
Max. paper thickness (μm)	80	80
Paper loading	Automatic	Automatic
Printing speed (mm/s)	75	120
Paper detection	Opto sensor	Opto sensor
Temperature detection	Thermistor	Thermistor
Head-up or Cover-open detection	Switch	Switch
	Switch.	Switch
Voltage range (Logic Head)	5 ± 5% V 4.2-8.5 V	5 ± 5% V 18-26.5 V
·		
Voltage range (Logic Head)	5 ± 5% V 4.2-8.5 V	5 ± 5% V 18-26.5 V
Voltage range (Logic Head) Dot resistance (Ohm)	5 ± 5% V 4.2-8.5 V 176 ± 3%	5 ± 5% V 18-26.5 V 1500 ± 3%
Voltage range (Logic Head) Dot resistance (Ohm) Energy per dot (mJ)	5 ± 5% V 4.2-8.5 V 176 ± 3% 0.31	5 ± 5% V 18-26.5 V 1500 ± 3% 0.25
Voltage range (Logic Head) Dot resistance (Ohm) Energy per dot (mJ) Stepper motor (Ohm)	5 ± 5% V 4.2-8.5 V 176 ± 3% 0.31 Bipolar (13)	5 ± 5% V 18-26.5 V 1500 ± 3% 0.25 Bipolar (150)
Voltage range (Logic Head) Dot resistance (Ohm) Energy per dot (mJ) Stepper motor (Ohm) Weight (g)	5 ± 5% V 4.2-8.5 V 176 ± 3% 0.31 Bipolar (13)	5 ± 5% V 18-26.5 V 1500 ± 3% 0.25 Bipolar (150) 150
Voltage range (Logic Head) Dot resistance (Ohm) Energy per dot (mJ) Stepper motor (Ohm) Weight (g) Life/reliability	5 ± 5% V 4.2-8.5 V 176 ± 3% 0.31 Bipolar (13) 135 100km/100M pulses	5 ± 5% V 18-26.5 V 1500 ± 3% 0.25 Bipolar (150) 150 100km/100M pulses





- Compact but very rugged design (20 mm high, only 120 mm wide and 55 mm deep)
- Front or bottom paper loading
- Available as a two station option with paper roll widths of 2x39
- 24V printer features up to 120 mm/s printing speed

Applications

- Cash registers
- EFT POS
- Fiscal printers
- Gaming and lottery
- Measuring instruments and analysers
- Medical equipment
- Ticketing
- Weighing scales

Options

- $\bullet \ \mathsf{Chip} \ \mathsf{Set}$
- CSM05/24
- Cutter
- Rewinder
- Controller Board

